

Alarm Code 993-4
Restore 993-5

LOCATION: **B 911 (Westinghouse)**

SYSTEM: **WESTINGHOUSE MOTOR-GENERATOR OIL PIT**

- ACTION:**
- 1. CONTACT THE SIEMENS WATCH PERSON**
 - a. INFORM HIM THAT THE WESTINGHOUSE OIL PIT ALARM HAS JUST COME IN AND AN INSPECTION OF THE WESTINGHOUSE OIL PIT IS NEEDED IMMEDIATELY.**
 - b. IT IS DETERMINED THAT THERE IS REAL LEAK, THE WESTINGHOUSE MOTOR GENERATOR, IF RUNNING, MUST BE TURNED OFF (CB-52 OPENED) AND THE BRAKE APPLIED TO STOP THE MG SET IN 3 MINUTES.**
 - 2. THE SYSTEM ENGINEERS (MECH. AND ELECTRICAL) MUST BE NOTIFIED AS WELL AS THE SYSTEMS GROUP LEADER. DEPENDING ON THE AMOUNT AND ORIGIN OF THE LEAK WILL DETERMINE WHO ELSE ALSO HAS TO GET INVOLVED.**

[Back to Top](#)

Alarm Code 993-6
Restore 993-7

Location: B 911 (Westinghouse)

System: MCR UPS

Action:

1. **Check status**
 - a) **UPS is working on Battery Back-up**
 - b) **UPS is working in the Bypass Mode**
 - c) **UPS is not working**

2. **If UPS is in "A or C", see note 3**

3. **If UPS is in "B" proceed as follows:**
 - a) **Move rotary switch CCW to position 1, then to position 2**
 - b) **Follow instructions on the display panel.**
 - c) **If the UPS cannot be restored to normal operations then see note 3.**
 - d) **If the UPS is restored to normal operations then fill out Action Please for information only.**

Notes:

1. **Record Actions Taken**
2. **MCR = Main Control Room (x 4662)**
3. **Call UPS Tech from "Call In" List**
4. **CAS = Collider/Accelerator Support Group (x2024)**

[Back to Top](#)